

GREEN POWER 40 CHANNEL BATTERY CHARGER



2WL VRLA Battery Charger Model : GP-MXV-40

Current 2 Amps / 4 Amps
with 5 hours Charging cycle



2WL Flooded Battery Charger Model : GP-MXF-40

Current 2 Amps / 4 Amps
with 5 hours Charging cycle



3WL Flooded Battery Charger Model GP-MX-ARF-40

Current 2.5 Amps / 5 Amps
with 10 hours Charging cycle.



Main Features :

- Customised Battery Charger with separate Charge Panel & detachable 40 block Charging Station suitable to charge 40 units of Batteries at a time.
- 3 Stage Charging profile with Recovery, Absorption & Float mode.
- Following are LED indications :
 - a) LED Light : Power On/Module OK (Blue colour)
 - b) Charging Current (Green Colour)
 - c) Bad Battery (Red Colour)
 - d) Connection Polarity (Yellow Colour)
 - e) Charge Finish (Green Colour)

Technical Specifications:

- Input Voltage AC : 90 – 270 VAC, 50 Hz, Single Phase
- Output Voltage : 12 VDC (Single Channel)
- Output Current : 2 A / 4 A (Selection)
for 2WL VRLA / Flooded Batteries
- Output Current : 2.5 A & 5.0A (Selection)
for 3WL Flooded Batteries.
- Protections : Input under Voltage, Over Voltage, Over Load, Short Circuits etc.
- MCB Protection : 40 Amps & 415 Volts
- Cooling Type : Force Cooling
- Storage Temperature : -50°C to 80°C

- Charger Rack Dimension : L 137.4 cm X W 32 cm X H 82.5 cm
- Battery Rack Dimension : L 195 cm X W 107 cm X H 86.5 cm
- Total Gross Wt. : 310 kgs with export packing
(one charger + one platform)

Key Benefits :

- Single button & user friendly operation.
- Facilitates smart charging process in easy & efficient manner.
- Charge Finish & Easy visual indication for operators.
- Once the batteries are charged the channel station can be detached and betowed to the stocking point easily.
- Additional channel station is available.
- Easy service & maintenance of product.
Replacement of defective model can be done by unscrewing just 2/3 screws.



APPLE ENERGY PVT. LTD.

314 & 406, Hilton Centre, Sector - 11, CBD Belapur,
Navi Mumbai - 400614, India. Tel. : +91-22-27564032 / 33,
E-mail : marketing@appleenergy.in

HELPLINE :

Sales : +91-8080806938 / 48
Service : +91-8080806918 / 28